

Integrated Optics, UAB Company code: 302833442 VAT No: LT100007179012 https://integratedoptics.com info@integratedoptics.com



PART NUMBER 0785L-44A ITEM NAME 785 NM NARROW LINEWIDTH LASER (HP VBG DIODE; MM FIBER)

# PRODUCT DATASHEET



#### DESCRIPTION

High power 785 nm narrow spectrum laser for industrial Raman applications. Fiber coupled to a multimode fiber which results in circular, nearly top-hat homogeneous beam output. This high-power SLM laser found its applications in industrial Raman Spectroscopy and other sensing applications. Despite its high output power, this ultra-compact self-contained laser module can be used the same way as any other laser in the MatchBox series. Stainless steel fiber jacket ensures robustness in harsh industrial environments. This 785 nm unit features good center wavelength stability and wide operational temperature range.

#### Note:


Specifications updated: 25 October 2021

In optical systems with strong back-reflections (e.g. more than 10%), the laser must be protected by using an optical isolator with at least 20 dB isolation. Typical applications include interferometry, confocal microscopy (especially working with reflective samples), etc. Failure to comply with these requirements will render the warranty void for cases of COD (Catastrophic Optical Damage) of laser diode facets.

**TYPICAL SPECTRUM** 


## SPECIFICATIONS

Parameter	Minimum Value	Typical Value	Maximum Value
Central Wavelength, nm	784.5	785	785.5
Longitudinal modes	-	Narrow Spectrum	-
Spectral line width FWHM, pm	30	50	80
Output power, mW	-	450 <sup>1</sup>	-
Side-mode suppression ratio (SMSR), dB	40	50	60
Power stability, % (RMS, 8 hrs)	-	1 <sup>2</sup>	2
Power stability, % (peak-to-peak, 8 hrs)	-	2 <sup>3</sup>	3
Intensity noise, % (RMS, 20 Hz to 20 MHz)	-	0.3 <sup>4</sup>	1
Control interface type	-	UART <sup>5</sup>	-
Transversal modes	-	Multiple	-
Operation mode	-	APC (CW)	-
Modulation bandwidth, MHz	-	N/A <sup>6</sup>	-
Input voltage, VDC	4.8	5	5.3
External power supply requirement	-	+5 V DC, 1.5 A	-
Dimensions, mm	-	$50 \times 30 \times 18^{7}$	-
Fiber Length, m	0.95	1	1.1
Heat-sinking requirement, °C/W	-	1	-
Optimum heatsink temperature, °C	15	20	30
Warm up time, mins (cold start)	0.2	1	2
Temperature stabilization	-	Internal TEC	-
Overheat protection	-	Yes	-




Typical spectrum of 0785 nm diode laser. Measured with 20 pm resolution.


## TYPICAL NEAR FIELD



Storage temperature, °C (non- condensing)	-10	-	50
Net weight, kg	0.1	0.12	0.14
Max. power consumption, W	0.4	2	10
Warranty, months (op. hrs)	-	14 (10000) <sup>8</sup>	-
RoHS	-	Yes	-
CE compliance	-	- General Product Safety Directive (GPSD) 2001/95/EC - (EMC) Directive 2004/108/EC	-
Laser Safety Class	-	3B	-
OEM lasers are not compliant with	-	IEC60825- 1:2014 (compliant using additional accessories)	-
Country of origin	-	Lithuania	-

#### DRAWING





2.54

3.8 Ø0.76

<sup>1</sup> The output power of SLM lasers shall not be tuned and SLM performance is not guaranteed at power ratings other than factory preset. However, the power setting capability is not disabled. External attenuators are recommended instead.

 $^2$  The long term power test is carried out at constant laser body temperature (+/-0.1 °C) using an optical power meter with an input bandwidth of 10 Hz. The actual measurement rate has a period of about 20 seconds to 1 minute.

<sup>3</sup> The long term power test is carried out at constant laser body temperature (+/-0.1 °C) using an optical power meter

with an input bandwidth of 10 Hz. The actual measurement rate has a period of about 20 seconds to 1 minute. <sup>4</sup> Noise level is measured with a fast photodiode connected to an oscilloscope. The overall system bandwidth is from 2 kHz to 20 MHz.

<sup>5</sup> Break-out-boxes AM-C8 and AM-C3 can be used for conversion of UART communication to either USB or RS232.

<sup>6</sup> SLM lasers shall not be modulated - use external modulators instead.

<sup>7</sup>Excluding control interface pins and an output window/fiber assembly.

<sup>8</sup>Whichever occurs first. The laser has an integrated operational hours counter.

Note: Product specifications are subject to change without prior notice to improve reliability, function or design or otherwise.